



FAB & RAF Screwdrivers | Torque range 0.4 – 44 in-lb

FAB & RAF screwdrivers have been well-known in the electronic industry since we first developed them in the early 1990s. FAB and RAF series are Kolver®'s powerful, reliable and truly cost-effective tools.

Quick to set up, easy to use

FAB and RAF tools are incredibly easy to install and operate. The torque is set externally: you'll only have to turn the clutch adjusting nut according to the required torque setting. Each screwdriver works in combination with a control unit. Its electronic control circuit cuts the power supply to the screwdriver motor in response to the clutch action as soon as the pre-set torque has been reached.

Simple maintenance

Replacing carbon brushes and greasing the gears once a year is all you need for maintenance. EDU1FR control units for FAB and RAF screwdrivers feature a maintenance-free, state-of-the-art electronics and no wearing components. This design results in very low current to the driver's start switch and clutch switch to extend their life indefinitely.

Safe, clean and low noise

All FAB and RAF models come standard with ESD-safe housings against electrostatic discharge. Their electric motor makes them not only energy efficient but also free of pollutants and contributes to a quieter environment (noise within 55 dB(A)). Ergonomic grip, lightweight and compact design for maximum operator comfort.


Basic and advanced functionalities

FAB and RAF work in combination with EDU1FR series controllers, acting as an AC to DC transformer and torque controller with adjustable slow start and speed. More features available when used in combination with EDU2AE/FR controller or EDU1FR/SG with ACE screw counter (see chart on next page).


Available Housings



INLINE – Inline versions available in lever start or push-to-start.
Bit Drive: 1/4" hex quick change chuck



PISTOL GRIP – Trigger start, pistol grip available with top connector (PP/FR/U) or bottom connector (PP/FR).
Bit Drive: 1/4" hex quick change chuck



ANGLE HEAD OPTION – 90° angle heads can be easily attached to inline models. Angle attachments are the ideal solution to operate where space is limited. See page 48.





Inline FAB Screwdrivers

Code	Model	Torque in-lb	RPM min-max	Dimensions in	Weight lb	Start Option
110003/FR	FAB03SS/FR	0.4 - 2.7	450 - 650	9.3 x 1.3	1.1	Lever Start
110010/FR	FAB10RE/FR	0.4 - 7	600 - 1000	9.3 x 1.3	1.1	Lever Start
110012/FR	FAB12RE/FR	1.8 - 10.6	600 - 1000	9.3 x 1.3	1.1	Lever Start
112012/FR	FAB12PS/FR	1.8 - 10.6	600 - 1000	9.8 x 1.3	1.1	Push-to-start
110618/FR	FAB18RE/FR	2.7 - 16	450 - 650	9.3 x 1.3	1.1	Lever Start
112618/FR	FAB18PS/FR	2.7 - 16	450 - 650	9.8 x 1.3	1.1	Push-to-start

Inline RAF Screwdrivers

Code	Model	Torque in-lb	RPM min-max	Dimensions in	Weight lb	Start Option
120032/FR	RAF32NS/FR	6.2 - 28.3	600 - 1000	10.2 x 1.6	1.4	Lever Start
122032/FR	RAF32PS/FR	6.2 - 28.3	600 - 1000	10.6 x 1.6	1.4	Push-to-start
120638/FR	RAF38NS/FR	8 - 33.6	450 - 650	10.2 x 1.6	1.4	Lever Start
122638/FR	RAF38PS/FR	8 - 33.6	450 - 650	10.6 x 1.6	1.4	Push-to-start
120650/FR	RAF50NS/FR	8 - 44.3	400 - 700	10.2 x 1.6	1.4	Lever Start
122650/FR	RAF50PS/FR	8 - 44.3	400 - 700	10.6 x 1.6	1.4	Push-to-start

Pistol grip FAB Screwdrivers

Code	Model	Torque in-lb	RPM min-max	Dimensions in	Weight lb	Connector Option
110013/FR	FAB12PP/FR	1.8 - 10.6	600 - 1000	8.7 x 6.3 x 1.7	1.1	Bottom connector
110013/FR/U	FAB12PP/FR/U	1.8 - 10.6	600 - 1000	8.7 x 6.4 x 1.7	1.1	Top connector
110619/FR	FAB18PP/FR	2.7 - 16	450 - 650	8.7 x 6.3 x 1.7	1.1	Bottom connector
110619/FR/U	FAB18PP/FR/U	2.7 - 16	450 - 650	8.7 x 6.4 x 1.7	1.1	Top connector

Pistol grip RAF Screwdrivers

Code	Model	Torque in-lb	RPM min-max	Dimensions in	Weight lb	Connector Option
120033/FR	RAF32PP/FR	6.2 - 28.3	600 - 1000	8.7 x 6.3 x 1.7	1.4	Bottom connector
120033/FR/U	RAF32PP/FR/U	6.2 - 28.3	600 - 1000	8.7 x 6.4 x 1.7	1.4	Top connector
120639/FR	RAF38PP/FR	8 - 33.6	450 - 650	8.7 x 6.3 x 1.7	1.4	Bottom connector
120639/FR/U	RAF38PP/FR/U	8 - 33.6	450 - 650	8.7 x 6.4 x 1.7	1.4	Top connector
120651/FR	RAF50PP/FR	8 - 44.3	400 - 700	8.7 x 6.3 x 1.7	1.5	Bottom connector
120651/FR/U	RAF50PP/FR/U	8 - 44.3	400 - 700	8.7 x 6.4 x 1.7	1.5	Top connector

Control units for FAB & RAF Screwdrivers

Code	Model	Adjustable Speed	Ramp Option	I/O Signals	Serial Print	Screw Count	Run Time	Weight lb	Dimensions in
010010/FR	EDU1FR	•	•	-	-	-	-	1.3	5.4 x 4.6 x 2.6
010010/FR/SG	EDU1FR/SG	•	•	•	with ACE	with ACE	-	1.3	5.4 x 4.6 x 2.6
032000/FR	EDU2AE/FR	•	•	•	•	•	•	5.3	7.7 x 6.7 x 4.3

2D and 3D drawings available on kolver.it

IMPORTANT: Continuous use over 80% of torque range is not recommended.